MO132-10



Products Low Voltage Products and Systems Circuit Breakers Manual Motor Starters

Products Low Voltage Products and Systems Control Products Manual Motor Starters Manual Motor Starters

General Information

Extended Product Type: MO132-10

Product ID: 1SAM360000R1010 **EAN:** 4013614400254

Catalog Description: MO132-10 Manual Motor Starter Magnetic Only

Long Description: The MO132-10 manual motor starter mangnetic only is a compact 45 mm width devices wit

h a rated operational current of le = 10.0 Å. This device is used to manually switch on and off loads/motors and to protect them reliably and without the need for a fuse from short-circ uits. The manual motor starter offers a rated service short-circuit breaking capacity lcs = 5 0 kA at 400 VAC. A combination together with overload relays or motor controllers allows th e protection of motors. Further features are the build-in disconnect function, trip-free mech anism and a rotary handle with a clear switch position indication. The manual motor starter mangnetic only is suitable for three- and single-phase applications. The handle is lockable to protect against unauthorized changes. Auxiliary contacts, signalling contacts, undervolta ge releases, shunt trips, 3-phase bus bars, power in-feed blocks are available as accessor

у.

Additional Information

| ABS Certificate: | 1SAA963001-0101 |
|---|---|
| Actuator Type: | Rotary Handle |
| Ambient Air Temperature: | Around the Enclosure 0 +40 °C Operation -25 +60 °C Storage -50 +80 °C |
| Ambient Air Temperature Compensation: | No |
| Ampere Rating UL/CSA: | 10 A |
| BV Certificate: | 1SAA963001-0201 |
| CB Certificate: | 1SAA963002-2001 |
| CCC Certificate: | 1SAA963001-3805 |
| Connecting Capacity Main Circuit UL/CSA: | Flexible 1/2x 16-12 AWG Stranded 1/2x 16-12 AWG |
| Connecting Capacity Main Circuit: | Flexible with Ferrule 1/2x 0.75 2.5 mm ² Flexible with Insulated Ferrule 1/2x 0.75 2.5 mm ² Flexible 1/2x 0.75 2.5 mm ² Rigid 1/2x 1 4 mm ² |
| Contact Position Indication: | ON / OFF / TRIP |
| Conventional Free-air Thermal Current (I _{th}): | Main Circuit 10 A |
| Country of Origin: | Germany (DE) |
| Customs Tariff Number: | 85362010 |
| DNV Certificate: | 1SAA963001-0302 |
| Data Sheet, Technical Information: | 2CDC131035D0201 |
| Data Sheet, Technical Information (Part 2): | 1SAM300515F0008 |
| Declaration of Conformity - CE: | 1SAD938504-0183 |
| Degree of Protection: | Housing IP20 Main Circuit Terminals IP10 |
| E-nummer: | 3110038 |
| EAC Certificate: | 1SAA963000-2701 |
| | |
| EAN: | 4013614400254 |

| EPLAN Function Definition: | Motor overload switch / Motor overload switch, 6 connection points / Motor overload switch thr ee-pole 1_2_3_4_5_6 |
|---|--|
| ETIM 4: | EC000074 - Motor protective circuit-breaker |
| ETIM 5: | EC000074 - Motor protective circuit-breaker |
| ETIM 6: | EC000074 - Motor protection circuit-breaker |
| Electrical Durability: | 50000 cycle |
| Frequency (f): | 0 400 Hz |
| GL Certificate: | 1SAA963001-0401 |
| GOST Certificate: | 1SAA963001-2702 |
| General Use Rating UL/CSA: | (600 V AC) 10 A |
| Horsepower Rating UL/CSA: | (220 240 V AC) Three Phase 3 Hp (440 480 V AC) Three Phase 5 Hp (550 600 V AC) Three Phase 7.5 Hp |
| Instructions and Manuals: | 2CDC131034M6801 |
| Invoice Description: | MO132-10 Manual Motor Starter Magnetic only, 10A |
| LR Certificate: | 1SAA963001-0502 |
| Maximum Operating Altitude Permissible: | 2000 m |
| Maximum Operating Voltage UL/CSA: | Main Circuit 600 V AC |
| Mechanical Durability: | 100000 cycle |
| Minimum Order Quantity: | 1 piece |
| Mounting Position: | Position 1 to 6 |
| Mounting on DIN Rail: | TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715 |
| Number of Poles: | 3 |
| Number of Protected Poles: | 3 |
| Object Classification Code: | F |
| Package Level 1 Gross Weight: | 0.28 kg |
| Package Level 1 Height: | 50 mm |
| Package Level 1 Length: | 95 mm |
| Package Level 1 Units: | 1 piece |
| Package Level 1 Width: | 92 mm |
| Package Level 2 EAN: | 4013614443701 |
| Package Level 2 Gross Weight: | 11.586 kg |
| Package Level 2 Height: | 210 mm |
| Package Level 2 Length: | 395 mm |
| Package Level 2 Units: | 40 piece |
| Package Level 2 Width: | 280 mm |
| Phase Loss Sensitive: | No |
| Pollution Degree: | 3 |
| Power Loss: | at Rated Operating Conditions per Pole 2.2 W |
| Product Main Type: | MO132 |
| Product Name: | Manual Motor Starter Magnetic Only |
| Product Net Depth: | 86.75 mm |
| Product Net Height: | 90 mm |
| Product Net Weight: | 0.265 kg |
| Product Net Width: | 45 mm |
| RINA Certificate: | 1SAA963000-0802 |
| RMRS Certificate: | 1SAA918000-0703 |
| Rated Current (I _n): | 10 A |
| Rated Frequency (f): | Main Circuit 50 Hz |

| | Mail Oroak oo 12 |
|--|---|
| | Main Circuit 60 Hz |
| Rated Impulse Withstand Voltage (U_{imp}): | Main Circuit 6 kV |
| Rated Instantaneous Short-Circuit Current Setting (I_i): | 125 A |
| Rated Insulation Voltage (U _i): | 690 V |
| Rated Operational Current (I _e): | 10 A |
| Rated Operational Current AC-3 (I _e): | 10 A |
| Rated Operational Power AC-3 (P _e): | (400 V) Three Phase 4 kW |
| Rated Operational Voltage: | Main Circuit 690 V AC |
| Rated Service Short-Circuit Breaking Capacity (I _{cs}): | (230 V AC) 50 kA (400 V AC) 50 kA (440 V AC) 20 kA (500 V AC) 20 kA (690 V AC) 3 kA |
| Rated Ultimate Short-Circuit Breaking Capacity (I _{cu}): | (230 V AC) 50 kA (400 V AC) 50 kA (440 V AC) 20 kA (500 V AC) 20 kA (690 V AC) 3 kA |
| Rated Uninterrupted Current (I _u): | 10 A |
| Recommended Screw Driver: | Pozidriv 2 |
| Remarks: | For overload protection of the motors, an appropriate thermal or electronic overload relays m ust be used |
| Resistance to Shock acc. to IEC 60068-2-27: | 11 ms Pulse 25g |
| Resistance to Vibrations acc. to IEC 60068-2-6: | 5g / 3 150 Hz |
| RoHS Date: | 0159 |
| RoHS Information: | 1SAA963002-4405 |
| RoHS Status: | Following EU Directive 2002/95/EC August 18, 2005 and amendment |
| Selectivity Category: | A |
| Selling Unit of Measure: | piece |
| Setting Range: | None |
| Short Description: | MO132-10 Manual Motor Starter |
| Short-Circuit Protective Devices: | gG Type Fuses 100 A, 440 V AC gG Type Fuses 100 A, 500 V AC |
| Standards: | IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 UL 60947-1 UL 60947-4-1 |
| Suitable for Isolation: | Yes |
| Terminal Type: | Screw Terminals |
| Tightening Torque: | Main Circuit 0.8 1.2 N·m |
| Tightening Torque UL/CSA: | Main Circuit 10 in·lb |
| Trip Class: | None |
| UL Certificate: | UL_E137861 UL_E345003 |
| UNSPSC: | 39121521 |
| Utilization: | Starter Protection |
| Wire Stripping Length: | Main Circuit 9 mm |
| cUL Certificate: | cUL_E137861 cUL_E345003 |

cULus Certificate: cUL_E137861

eClass: 7.0 27370401