MS116-0.63



ProductsLow Voltage Products and SystemsCircuit BreakersManual Motor StartersProductsLow Voltage Products and SystemsControl ProductsManual Motor StartersManual Motor StartersParts & ServicesDrivesMedium voltage AC drivesIndustrial drivesACS2000Parts & ServicesDrivesMedium voltage AC drivesSpecial purpose drivesACS1000

General Information			
Extended Product Type:	MS116-0.63		
Product ID:	1SAM250000R1004		
EAN:	4013614320279		
Catalog Description:	MS116-0.63 Manual Motor Starter		
Long Description:	The MS116-0.63 manual motor starter is a compact 45 mm width devices with a rated oper ational current of le = 0.63 A. This device is used to manually switch on and off motors and to protect them reliably and without the need for a fuse from short-circuits, overload and ph ase failures. The manual motor starter offers a rated service short-circuit breaking capacity lcs = 50 kA at 400 VAC and the trip class 10A. Further features are the build-in disconnect function, temperature compensation, trip-free mechanism and a rotary handle with a clear switch position indication. The manual motor starter is suitable for three- and single-phase applications. Auxiliary contacts, signalling contacts, undervoltage releases, shunt trips, 3-p hase bus bars, power in-feed blocks and locking devices for protection against unauthorize d changes are available as accessory.		

Additional Information

ABS Certificate:	1SAA963000-0104		
Actuator Type:	Rotary Handle		
Ambient Air Temperature:	Around the Enclosure 0 +40 °C Operation -25 +70 °C Operation Compensated -25 +55 °C Storage -50 +80 °C		
Ambient Air Temperature Compensation:	Yes		
Ampere Rating UL/CSA:	0.63 A		
BV Certificate:	1SAA963000-0204		
CB Certificate:	1SAA963000-2003		
CCC Certificate:	1SAA963000-3804		
Connecting Capacity Main Circuit UL/CSA:	Flexible 1/2x 16-12 AWG Stranded 1/2x 16-12 AWG		
Connecting Capacity Main Circuit:	Flexible with Ferrule 1/2x 0.75 2.5 mm ² Flexible with Insulated Ferrule 1/2x 0.75 2.5 mm ² Flexible 1/2x 0.75 2.5 mm ² Rigid 1/2x 1 4 mm ²		
Contact Position Indication:	ON / OFF		
Conventional Free-air Thermal Current (I _{th}):	Main Circuit 0.63 A		
Core Credit:	0.00		
Country of Origin:	Germany (DE)		
Customs Tariff Number:	85362010		
DNV Certificate:	1SAA963000-0303		
Data Sheet, Technical Information:	2CDC131025D0201		
Data Sheet, Technical Information (Part 2):	1SAM200505F0004		
Data Sheet, Technical Information (Part 3):	1SAM200507F0001 1SAM200507F0002 1SAM200507F0003 1SAM200508F0001		

4041400050050000

	1SAM200508F0002 1SAM200508F0003			
Declaration of Conformity - CE:	1SAD938516-0060			
Degree of Protection:	Housing IP20			
	Main Circuit Terminals IP10			
Dimension Diagram:	1SAM200422F0001			
E-nummer:	3111936			
EAC Certificate:	1SAA963000-2701			
EAN:	4013614320279			
EPLAN Catalog Tree:	Electrical engineering / Protection devices / Motor overload switch			
EPLAN Function Definition:	Motor overload switch / Motor overload switch, 6 connection points / Motor overload switch thr ee-pole 1_2_3_4_5_6			
ETIM 4:	EC000074 - Motor protective circuit-breaker			
ETIM 5:	EC000074 - Motor protective circuit-breaker			
ETIM 6:	EC000074 - Motor protection circuit-breaker			
Electrical Durability:	100000 cycle			
Environmental Information:	1SAA963001-2401			
GL Certificate:	1SAA963000-0402			
GOST Certificate:	1SAA963001-2702			
General Use Rating UL/CSA:	(600 V AC) 0.63 A			
IIT Publishing Status:	Level 0 - Information enabled			
Industrial IT Certification Level:	0			
Instructions and Manuals:	2CDC131011M6802			
Invoice Description:	MS116-0.63 Manual Motor Starter Trip class 10A, 0.4 0.63A			
LR Certificate:	1SAA963000-0505			
Maximum Operating Altitude Permissible:	2000 m			
Maximum Operating Voltage UL/CSA:	Main Circuit 600 V AC			
Mechanical Durability:	100000 cycle			
Minimum Order Quantity:	1 piece			
Mounting Position:	Position 1 to 6			
Mounting on DIN Rail:	TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715			
Number of Poles:	3			
Number of Protected Poles:	3			
Object Classification Code:	F			
Package Level 1 EAN:	4013614320279			
Package Level 1 Gross Weight:	0.24 kg			
Package Level 1 Height:	50 mm			
Package Level 1 Length:	95 mm			
Package Level 1 Units:	1 piece			
Package Level 1 Width:	92 mm			
Package Level 2 EAN:	4013614408649			
Package Level 2 Gross Weight:	9.986 kg			
Package Level 2 Height:	210 mm			
Package Level 2 Length:	395 mm			
Package Level 2 Units:	40 piece			
Package Level 2 Width:	280 mm			
Part Type:	New			
Phase Loss Sensitive:	Yes			
Pollution Degree:	3			
-				

Power Loss:	at Rated Operating Conditions per Pole 0.7 1.7 W		
Product Main Type:	MS116		
Product Name:	Manual Motor Starter		
Product Net Depth:	85.6 mm		
Product Net Height:	90 mm		
Product Net Weight:	0.225 kg		
Product Net Width:	45 mm		
RMRS Certificate:	1SAA918000-0704		
Rated Current (In):	0.63 A		
Rated Frequency (f):	Main Circuit 50 Hz Main Circuit 60 Hz		
Rated Impulse Withstand Voltage (U_{imp}):	Main Circuit 6 kV		
Rated Instantaneous Short-Circuit Current Setting (I_i) :	7.9 A		
Rated Insulation Voltage (Ui):	690 V		
Rated Operational Current (Ie):	0.63 A		
Rated Operational Current AC-3 (I_e):	0.63 A		
Rated Operational Power AC-3 (P_e):	(400 V) Three Phase 0.18 kW		
Rated Operational Voltage:	Main Circuit 690 V AC		
Rated Service Short-Circuit Breaking Capacity (I _{cs}):	(230 V AC) 50 kA (400 V AC) 50 kA (440 V AC) 30 kA (500 V AC) 30 kA (690 V AC) 30 kA		
Rated Service Short-Circuit Breaking Capacity, in %of Icu (I _{cs}):	100 %		
Rated Ultimate Short-Circuit Breaking Capacity (I_{cu}) :	(230 V AC) 50 kA (400 V AC) 50 kA		
	(440 V AC) 30 kA (500 V AC) 30 kA (690 V AC) 30 kA		
Rated Uninterrupted Current (I _u):	(500 V AC) 30 kA		
Rated Uninterrupted Current (I _u): Recommended Screw Driver:	(500 V AC) 30 kA (690 V AC) 30 kA		
	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2-	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date: RoHS Information:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105 1SAA963001-4409		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date: RoHS Information: Selectivity Category:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105 1SAA963001-4409 A		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date: RoHS Date: RoHS Information: Selectivity Category: Selling Unit of Measure:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105 1SAA963001-4409 A piece		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date: RoHS Information: Selectivity Category: Selling Unit of Measure: Setting Range:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105 1SAA963001-4409 A piece 0.4 0.63 A		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date: RoHS Date: RoHS Information: Selectivity Category: Selling Unit of Measure: Setting Range: Short Description:	(500 V AC) 30 kA (690 V AC) 30 kA Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105 1SAA963001-4409 A piece 0.4 0.63 A MS116-0.63 Manual Motor Starter IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 UL 60947-1		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date: RoHS Information: Selectivity Category: Selling Unit of Measure: Setting Range: Short Description: Standards:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105 1SAA963001-4409 A piece 0.4 0.63 A MS116-0.63 Manual Motor Starter IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 UL 60947-1 UL 60947-4-1		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date: RoHS Information: Selectivity Category: Selling Unit of Measure: Setting Range: Short Description: Standards: Suitable for Isolation:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105 1SAA963001-4409 A piece 0.4 0.63 A MS116-0.63 Manual Motor Starter IEC/EN 60947-1 IEC/EN 60947-4-1 UL 60947-4-1 Yes		
Recommended Screw Driver: Resistance to Shock acc. to IEC 60068-2- 27: Resistance to Vibrations acc. to IEC 60068-2-6: RoHS Date: RoHS Information: Selectivity Category: Selling Unit of Measure: Setting Range: Short Description: Standards: Standards: Suitable for Isolation: Terminal Type:	(500 V AC) 30 kA (690 V AC) 30 kA 0.63 A Pozidriv 2 11 ms Pulse 25g 5g / 3 150 Hz 1105 1SAA963001-4409 A piece 0.4 0.63 A MS116-0.63 Manual Motor Starter IEC/EN 60947-1 IEC/EN 60947-1 UL 60947-4.1 UL 60947-4.1 Yes Screw Terminals		

UL Certificate:	UL_E137861
UNSPSC:	39121521
Utilization:	Motor Protection
Wire Stripping Length:	Main Circuit 9 mm
cUL Certificate:	cUL_E137861
eClass:	7.0 27370401
DNV GL Certificate:	1SAA963000-0303

Where Used (as a spare part for "Products")

2 Products

2 Products		Filter	
Identifier	Description	Qty	Unit Of Measure
ACS 1000	No Description Available	1	piece
ACS 2000	No Description Available	1	piece

Product specific part data

2 Products

Product	Category	Drive Part Category
ACS 2000	ACS2000	Switches, Relays, Contactors
ACS 1000	ACS1000	Switches, Relays, Contactors

Filter

