



Auxiliary contact

Part no.


FAZ-XHIN11

Article no.

286054



Delivery programme

For use with			FAZ PKNM
			Up to 63 A
Contacts		Number	1 N/O/1 N/C
Contact sequence			
Space units 1 SU = 18 mm		SU	0.5
Rated voltage		V	230 V
Number of N/O			1
Number of N/C			1
Number of changeover contacts			0
Fitted as standard			false
Space unit			0.5
Rated switch current		A	3 A
Number of fault signal switches			0
Device mounting			universal
Control voltage type			AC
Additional equipment			others

Electrical

Contact function			1 NO + 1 NC
Rated operational voltage	U_e	V AC	250
Rated frequency	f	Hz	50/60
Rated current	I_e	A	6
Conventional free air thermal current	I_{th}	A	6
Rated operational current			
AC--13			
250 V	I_e	A	3
AC-15	I_e	A	2 (250 V AC)
AC-12	I_e	A	3 (250 V AC)
DC-13	I_e	A	0.5 (110 V DC)
Rated insulation voltage	U_i	V AC	250
Minimum operating voltage per contact	U_{min}	V DC	5
Rated impulse withstand voltage	U_{imp}	kV	2.5
Rated conditional short-circuit current With 6 A back-up fuse	I_{sc}	kA	1
Max. admissible back-up fuse		A gL	6

Mechanical

Standard front dimension		mm	45
Enclosure height		mm	80
Mounting width		mm	8.8 (0.5 space unit)
Mounting			max. 2 × on MCB

Degree of protection			
Integrated			IP40
Terminal protection			Protection against electric shock to IEC 536
Terminals			Lift terminals
Terminal capacities		mm ²	
Solid		mm ²	0.5 ... 2.5
flexible		mm ²	0.5 ... 2.5
Tightening torque of terminal screws		Nm	≅ 1.2

Dimensions

