



## Main switch assembly kit, handle red, size 1

**Part no.** NZM1-XHBR  
**Article no.** 266632

### Delivery programme

|                              |  |   |
|------------------------------|--|---|
| Equipment supplied           |  | Door coupling rotary handle with rotary drive<br>NZM...-XV4 extension shaft<br>External warning plate/markings plate in German/English<br>Black and yellow lightning symbol   |
| Function                     |  | With red door coupling rotary handle for use of switch as emergency switching off device to IEC/EN 60204-1, VDE 0113 part 1   |
| Protection class             |  | IP66<br>UL/CSA Type 4X, Type 12   |
| Locking facility             |  | lockable on the 0 position on the switch using up to 3 padlocks   |
| Door interlock               |  | Door interlock on OFF with max. 3 padlocks<br>After the door interlock is activated, must not be opened while on ON or TRIP. Must only be opened on OFF<br>Can be modified such that it can be defeated from the outside using a screwdriver<br>Not defeated in the locked OFF position.<br>Can only be switched ON when the door is closed |
| Project planning information |  | External warning plate/designation label can be clipped on.<br>For enhanced busbar tag shroud on the incomer side, please order IP2X protection against contact with a finger.  |
| For use with                 |  | NZM1(-4)<br>PN1(-4), N(S)1(-4)  |

### Design verification as per IEC/EN 61439

|  |  |  |
|--|--|--|
| IEC/EN 61439 design verification   |  |  |
| 10.2 Strength of materials and parts   |  |  |
| 10.2.2 Corrosion resistance  |  | Meets the product standard's requirements.   |
| 10.2.3.1 Verification of thermal stability of enclosures   |  | Meets the product standard's requirements.   |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat   |  | Meets the product standard's requirements.   |
| 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects |  | Meets the product standard's requirements.   |
| 10.2.4 Resistance to ultra-violet (UV) radiation   |  | Meets the product standard's requirements.   |
| 10.2.5 Lifting   |  | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.6 Mechanical impact   |  | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.7 Inscriptions  |  | Meets the product standard's requirements.   |
| 10.3 Degree of protection of ASSEMBLIES  |  | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.4 Clearances and creepage distances   |  | Meets the product standard's requirements.   |
| 10.5 Protection against electric shock   |  | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.6 Incorporation of switching devices and components   |  | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.7 Internal electrical circuits and connections  |  | Is the panel builder's responsibility.   |
| 10.8 Connections for external conductors   |  | Is the panel builder's responsibility.   |
| 10.9 Insulation properties   |  |  |
| 10.9.2 Power-frequency electric strength   |  | Is the panel builder's responsibility.   |
| 10.9.3 Impulse withstand voltage   |  | Is the panel builder's responsibility.   |
| 10.9.4 Testing of enclosures made of insulating material   |  | Is the panel builder's responsibility.   |
| 10.10 Temperature rise   |  | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating   |  | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.12 Electromagnetic compatibility  |  | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.13 Mechanical function  |  | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.                         |

### Technical data ETIM 5.0

|   |  |     |
|---|--|-----|
| Low-voltage industrial components (EG000017) / Handle for power circuit breaker (EC000229)  |  |     |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Handle for switch devices (ecl@ss8-27-37-04-14 [AKF012010]) |  |     |
| Lockable  |  | Yes |

|                                    |  |     |
|------------------------------------|--|-----|
| Colour                             |  | Red |
| Suitable for emergency stop        |  | Yes |
| With axe                           |  | Yes |
| Suitable for power circuit breaker |  | Yes |
| Suitable for switch disconnecter   |  | Yes |

## Approvals

|                             |  |   |
|-----------------------------|--|---|
| Product Standards           |  | UL489; CSA-C22.2 No. 5-09; IEC60947, CE marking |
| UL File No.                 |  | E140305   |
| UL Category Control No.     |  | DIHS  |
| CSA File No.                |  | 022086  |
| CSA Class No.               |  | 1437-01   |
| North America Certification |  | UL listed, CSA certified                        |
| Degree of Protection        |  | IEC: IP66, UL/CSA Type 4X, 12                   |

## Additional product information (links)

|   |   |
|---|---|
| <b>IL01203005Z (AWA1230-1998) Door coupling rotary handle</b> |   |
| IL01203005Z (AWA1230-1998) Door coupling rotary handle        | <a href="ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL01203005Z2014_07.pdf">ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL01203005Z2014_07.pdf</a> |
| <b>IL01219050Z (AWA1230-2055) Main switch assembly kit</b>    |   |
| IL01219050Z (AWA1230-2055) Main switch assembly kit           | <a href="ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL01219050Z2011_02.pdf">ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL01219050Z2011_02.pdf</a> |