



Main

Range of product	Phaseo
Product or component type	Power supply
Power supply type	Regulated switch mode
Input voltage	100...120 V AC single phase, terminal(s): N-L1 200...500 V AC phase to phase, terminal(s): L1-L2
Output voltage	24 V DC
Rated power in W	72 W
PFC filter	With PFC filter conforming to IEC 61000-3-2
Power supply output current	3 A
Output protection type	Against overload, protection technology: manual or automatic reset Against overvoltage, protection technology: 30...32 V, manual reset Against short-circuits, protection technology: manual or automatic reset Against undervoltage, protection technology: tripping if $U < 21.6$ V Thermal, protection technology: automatic reset
Ambient air temperature for operation	-25...60 °C without derating

Complementary

Input voltage limits	170...550 V 85...132 V
Network frequency	47...63 Hz
Inrush current	≤ 30 A for 2 ms
Cos phi	0.51 at 240 V 0.59 at 120 V
Efficiency	87...100 %
Output voltage limits	24...28.8 V adjustable
Power dissipation in W	7.8 W
Line and load regulation	1...3 %
Residual ripple	≤ 200 mV
Holding time	≥ 120 ms at 400 V ≥ 20 ms at 100 V ≥ 40 ms at 240 V
Permissible temporary current boost	1.5 x I_n for 4 s
Connections - terminals	Screw type terminals for input connection, connection capacity: 3 x 0.5...3 x 4 mm ² AWG gauge22...12 Screw type terminals for input ground connection, connection capacity: 1 x 0.5...1 x 4 mm ² AWG gauge22...12 Screw type terminals for output connection, connection capacity: 4 x 0.5...4 x 4 mm ² AWG gauge22...12 Screw type terminals for output ground connection, connection capacity: 1 x 0.5...1 x 4 mm ² AWG gauge22...12
Marking	CE
Mounting support	35 x 15 mm symmetrical DIN rail 35 x 7.5 mm symmetrical DIN rail
Operating position	Vertical
Output coupling	Parallel Series

Name of test	Conducted emissions on the power line conforming to EN 55022 Class B Electrostatic discharges conforming to EN/IEC 61000-4-2 Harmonic current emission conforming to EN/IEC61000-3-2 Induced electromagnetic field conforming to EN/IEC 61000-4-6 Magnetic field conforming to EN 61000-4-8 Primary outage conforming to IEC 61000-4-11 Radiated electromagnetic field conforming to EN/IEC 61000-4-3 Radiated emissions conforming to EN 55022 Class B Rapid transient conforming to IEC 61000-4-4 Surge conforming to EN/IEC 61000-4-5
Status LED	1 LED green and red for output voltage 1 LED green, red and orange for output current
Product weight	0.3 kg

Environment

Product certifications	CCSAus C-Tick UL
Environmental characteristic	EMC conforming to EN 61000-6-1 EMC conforming to EN 61000-6-3 EMC conforming to EN/IEC 61000-6-2 EMC conforming to EN/IEC 61000-6-4 EMC conforming to EN/IEC 61204-3 Safety conforming to EN/IEC 60950-1 Safety conforming to EN/IEC 61204-3 Safety conforming to SELV
IP degree of protection	IP20 conforming to EN/IEC 60529
Ambient air temperature for storage	-40...70 °C
Relative humidity	0...90 % during operation 0...95 % in storage
Class of protection against electric shock	Class I conforming to VDE 0106-1
Dielectric strength	3500 V between input and ground 4000 V between input and output 500 V between output and ground
RoHS EUR status	Compliant
RoHS EUR conformity date	0501

Regulated Switch Mode Power Supplies

Dimensions

ABL 8	a in mm	a in in.	b in mm	b in in.
RPS24030	120	4.72	44	1.73
RPS24050	120	4.72	56	2.20
RPS24100	140	5.51	85	3.34
RPM24200	140	5.51	145	5.70
WPS24200	155	6.10	95	3.74
WPS24400	155	6.10	165	6.49

Regulated Switch Mode Power Supply

Internal Wiring Diagram

Regulated Switch Mode Power Supply

Line Supply Wiring Diagram

Single-phase (L-N) 100 to 120 V

Phase-to-phase (L1-L2) 200 to 500 V

Single-phase (L-N) 200 to 500 V

Regulated Switch Mode Power Supplies

Series or Parallel Connection

Series Connection

(1) Two Schottky diodes I_{min} = power supply I_n and V_{min} = 50 V

Parallel Connection

Family	Series	Parallel
ABL 8RPS/8RPM/8WPS	2 products max. (1)	2 products max.

Series or parallel connection is only recommended for products with identical references.

For better availability, the power supplies can also be connected in parallel using the ABL8RED24400 Redundancy module.

Regulated Switch Mode Power Supplies

Derating

The ambient temperature is a determining factor that limits the power an electronic power supply can deliver continuously. If the temperature around the electronic components is too high, their life will be significantly reduced.

The nominal ambient temperature for the Universal range of Phaseo power supplies is 50°C. Above this temperature, derating is necessary up to a maximum temperature of 60°C.

The graph below shows the power (in relation to the nominal power) that the power supply can deliver continuously, depending on the ambient temperature.

X Maximum operating temperature (°C)

ABL 8RPM, ABL 8RPS, ABL 8WPS mounted vertically

Derating should be considered in extreme operating conditions:

- Intensive operation (output current permanently close to the nominal current, combined with a high ambient temperature)
- Output voltage set above 24 Vdc (to compensate for line voltage drops, for example)
- Parallel connection to increase the total power

Regulated Switch Mode Power Supply

Load Limit

Manual Reset Protection Mode

(1) Boost 4s

Automatic Reset Protection Mode

(1) Boost 4s

"Boost" Repeat Accuracy

This type of operation is described in detail in the user manual, which can be downloaded from the website.