

GAMMA INSTABUS POWER SUPPLY N 125/21 640MA,
INTEGRATED REACTOR, 4MW



Similar to image

| Technical data: | |
|---|--|
| Design type | voltage supplies |
| Type, explanations | N 125/21 voltage supply |
| Type, explanations / additionally | integrated reactor, 640 mA, additional output without reactor, 29 V DC |
| Type of mounting | modular installation device |
| Number of pitch units for width | 4 |
| Bus system / can be used / EIB/KNX | Yes |
| Bus system / usable / RF bus system | No |
| Bus system / usable / Powernet bus system | No |
| Bus system / usable / LON bus system | No |
| Output current | 640 |
| Rated operational voltage, AC | 120 to 230 |
| Output voltage, DC | V 29 |
| Number of installation bus lines | 1 |
| Number of chokes / integrated | 1 |
| Output current / maximum | mA 640 |
| Product component / Buffer battery | No |
| Product component / LED | Yes |

Certificates/approvals:

General Product Approval



Declaration of Conformity

Further information:

Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/lowvoltage/catalogs>

Industry Mall (Online ordering system)

<http://www.siemens.com/lowvoltage/mall>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<http://support.automation.siemens.com/WW/view/en/5WG1125-1AB21/all>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=5WG1125-1AB21

CAX-Online-Generator

<http://www.siemens.com/cax>

last change:

Mar 18, 2013