

SIMATIC DP, Interface module IM 151-1 Basic for ET 200S;
 Transmission rate to 12 Mbit/s; max. 12 power, electronic or motor
 starter modules (no F modules) can be connected; Bus connection
 via 9-pin D-sub incl. termination module



Figure similar

General information	
Vendor identification (VendorID)	80F3h
Supply voltage	
Mains buffering	
<ul style="list-style-type: none"> Mains/voltage failure stored energy time 	No
Input current	
from supply voltage 1L+, max.	70 mA
Power loss	
Power loss, typ.	1.5 W
Address area	
Addressing volume	
<ul style="list-style-type: none"> Inputs 	88 byte
<ul style="list-style-type: none"> Outputs 	88 byte
Interfaces	
Interface physics, RS 485	Yes; 9-pin sub D socket

PROFIBUS DP	
• Output current, max.	80 mA
• Transmission rate, max.	12 Mbit/s; 9,6 / 19,2 / 45,45 / 93,75 / 187,5 / 500 kbit/s; 1,5 / 3 / 6 / 12 Mbit/s
• SYNC capability	Yes
• FREEZE capability	Yes
• Direct data exchange (slave-to-slave communication)	Yes

Protocols

Supports protocol for PROFINET IO	No
PROFIBUS DP	Yes

Protocols (Ethernet)

• TCP/IP	No
----------	----

Isochronous mode

Isochronous operation (application synchronized up to terminal)	No
---	----

Interrupts/diagnostics/status information

Alarms	No
--------	----

Diagnostic functions	Yes
----------------------	-----

Diagnostics indication LED

• Bus fault BF (red)	Yes
• Group error SF (red)	Yes
• Monitoring 24 V voltage supply ON (green)	Yes

Potential separation

between backplane bus and electronics	No
---------------------------------------	----

between electronic block and PROFIBUS DP	Yes
--	-----

between supply voltage and electronics	No
--	----

Permissible potential difference

between different circuits	75 V DC/60 V AC
----------------------------	-----------------

Isolation

Isolation tested with	500 V DC
-----------------------	----------

Dimensions

Width	45 mm
-------	-------

Height	119.5 mm
--------	----------

Depth	75 mm
-------	-------

Weights

Weight, approx.	150 g
-----------------	-------

last modified: 07/30/2018