

MLFB-Ordering data

6SL3210-1PE11-8AL1



Client order no. : Order no. : Offer no. : Remarks :

Item no. :
Consignment no. :
Project :

Rated data		General tec	General tech. specifications	
Input		Power factor λ	0.85	
Number of phases	3 AC	Offset factor cos φ	0.95	
Line voltage	380 480 V ±10 %	Efficiency η	0.96	
Line frequency	47 63 Hz	Sound pressure level (1m)	72 dB	
Rated current (LO)	2.30 A	Power loss	0.04 kW	
Rated current (HO)	2.00 A	Ambient conditions		
Output		Cooling	Internal air cooling	
Number of phases	3 AC	Cooling air requirement	0.005 m³/s	
Rated voltage	400 V	Installation altitude	1000 m	
Rated power (LO)	0.55 kW / 0.75 hp	Ambient temperature		
Rated power (HO)	0.37 kW / 0.50 hp	Operation LO	-5 40 °C (23 104 °F)	
Rated current (LO)	1.70 A	Operation HO	-5 50 °C (23 122 °F)	
Rated current (HO)	1.30 A	Transport	-40 70 °C (-40 158 °F)	
Max. output current	2.60 A	Storage	-25 55 °C (-13 131 °F)	
Pulse frequency	4 kHz	Relative humidity		
Output frequency for vector control	0 200 Hz			
Output frequency for V/f control	0 550 Hz	Max. operation	95 % RH, condensation not permitted	

Overload capability

Low Overload (LO)

1.1 x rated output current (i.e. 110 % overload) for 57 s with a cycle time of 300 s 1.5 × rated output current (i.e. 150 % overload) for 3 s with a cycle time of 300 s

High Overload (HO)

1.5 × output current rating (i.e., 150 % overload) for 57 s with a cycle time of 300 s 2 × output current rating (i.e., 200 % overload) for 3 s with a cycle time of 300 s

SIEMENS Data sheet for SINAMICS Power Module PM240-2

MLFB-Ordering data

6SL3210-1PE11-8AL1

-79.03 %



Mechanical data Connections Degree of protection IP20 Line side Plug-in screw-type terminals Size FSA Version Net weight 1.50 kg Conductor cross-section 1.00 ... 2.50 mm² Width 73.0 mm Motor end Height 196.0 mm Version Plug-in screw terminals Depth 165.0 mm Conductor cross-section 1.00 ... 2.50 mm² Converter losses to EN 50598-2* Efficiency class IE2

 100%
 29.0 W (2.45 %)
 30.0 W (2.58 %)
 33.0 W (2.77 %)

 50%
 27.0 W (2.27 %)
 28.0 W (2.34 %)
 29.0 W (2.42 %)

 25%
 27.0 W (2.25 %)
 27 W (2.29 %)
 50%
 90%
 f

The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard EN 50598) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.

*calculated values; increased by 10% according to the standard

Comparison with the reference converter (90% /

100%)

Max. motor cable length

Shielded	50 m			
Unshielded	100 m			
Standards				
Compliance with standards	UL, cUL, CE, C-Tick (RCM), SEMI F47			
CE marking	Low-voltage directive 2006/95/EC			