

### General Information

<b>Extended Product Type:</b>	F204 A-25/0,3
<b>Product ID:</b>	2CSF204101R3250
<b>EAN:</b>	8012542783701
<b>Catalog Description:</b>	F204 A-25/0,3 Residual Current Dev.
<b>Long Description:</b>	The RCCBs F200 series assures protection to people and installations against fault current to earth. A large offer for standard instantaneous and selective AC and A types is completed with some configurations for special applications.

### Categories

Products » Low Voltage Products and Systems » Modular DIN Rail Products » Residual Current Devices RCDs » Residual Current Devices RCDs

### Ordering

<b>EAN:</b>	8012542783701
<b>Minimum Order Quantity:</b>	1 piece
<b>Customs Tariff Number:</b>	85363030

### Dimensions

<b>Product Net Width:</b>	0.070 m
<b>Product Net Height:</b>	0.085 m
<b>Product Net Depth:</b>	0.069 m
<b>Product Net Weight:</b>	0.360 kg

### Container Information

<b>Package Level 1 Units:</b>	1 piece
<b>Package Level 1 Width:</b>	0.082 m
<b>Package Level 1 Height:</b>	0.078 m
<b>Package Level 1 Length:</b>	0.096 m
<b>Package Level 1 Gross Weight:</b>	0.403 kg
<b>Package Level 1 EAN:</b>	8012542783701

### Technical

<b>Standards:</b>	IEC EN 61008
<b>Operating Characteristic:</b>	Instantaneous
<b>Type of Residual Current:</b>	A type
<b>Rated Residual Current:</b>	300 mA
<b>Rated Current (I<sub>n</sub>):</b>	25 A
<b>Number of Poles:</b>	4
<b>Position of Neutral Terminals:</b>	Right
<b>Power Loss:</b>	Per Pole 1.3 W
<b>Rated Voltage (U<sub>r</sub>):</b>	230/400 V

### Environmental

<b>RoHS Status:</b>	Planned to follow EU Directive 2002/95/EC August 18, 2005 and amendment after 2007 Q3
---------------------	---

### Certificates and Declarations (Document Number)

<b>Declaration of Conformity - CE:</b>	<a href="#">ITSCE116F200</a>
<b>RoHS Information:</b>	<a href="#">2CSC423001K0201</a>

### Classifications

<b>Object Classification Code:</b>	Q
<b>ETIM 4.0:</b>	EC000003 - Residual current circuit breaker (RCCB)
<b>ETIM 5.0:</b>	EC000003 - Residual current circuit breaker (RCCB)

