

Rittal – The System.

Faster – better – everywhere.

► Connection accessories for self- assembly for LED system light, connector/jack – SZ 2500.620

Date : Jan 21, 2022

ENCLOSURES

POWER DISTRIBUTION

CLIMATE CONTROL

IT INFRASTRUCTURE

SOFTWARE & SERVICES

FRIEDHELM LOH GROUP



Connection accessories for self-assembly for LED system light, connector/jack – SZ 2500.620

created: 21.01.2022 build on www.rittal.com/uk-en



Product description

Design: Jack, 2-pole

Product description

Dimensions: Width: 15.6 mm
Height: 13.2 mm
Depth: 61.6 mm

Rated operating voltage: 100 V - 240 V

Cable cross-sections: Nominal cross-section: 1.5 mm²
Connection of round conductors, single-wire: 0,25 mm² - 1,5 mm²
Connection of round conductors, single-wire: AWG 16 - AWG 22
Connection of round conductors, multi-wire: 0,25 mm² - 1 mm²
Connection of round conductors, multi-wire: AWG 18 - AWG 22

Min. cable diameter: 3.8 mm

Max. cable diameter: 8.2 mm

Packs of: 5 pc(s).

Weight/pack: 0.06 kg

Copper weight (kg per piece): 0

EAN: 4028177918757

Customs tariff number:	85369095
ETIM 7.0:	EC000458
ETIM 6.0:	EC000458
eCl@ss 8.0/8.1:	27440314
eCl@ss 6.0/6.1:	27260702
Product description:	SZ Jack, for power supply and through-wiring, 2-pole, 100-240 V, Connection accessories for self-assembly
Approvals	
Approvals:	UL + C-UL
Declarations:	Declaration of conformity Manufacturer's declaration