



TRANSFORMER SITAS;  
 PHASES:1;  
 PN/PN(S6)(KVA):1 /5;  
 UPRI(V):500+/-5%;  
 USEC(V):230;  
 ISEC(A):4,35;  
 F(HZ):50...60;  
 VECTOR GR./SHIELD WNG.:li0 /0;  
 TA/ISOKL:40 /B;  
 IP00;  
 TYPE OF TERMINALS:SCREW/TAB CONNECTION;  
 INSTALLATION:SCREW;  
 EN 61558-2-1, -2-2,  
 -2-4 >UL/CSA-RECOGNIZED< >CONTROL CIRCUIT  
 TRANSFORMER< >ISOLATION TRANSFORMER<

**General technical details:**

<b>product designation</b>		transformer SITAS
<b>Product brand name</b>		SIDAC
<b>Operating apparent output / rated value</b>	V·A	1,000
<b>Efficiency</b>		0.93
<b>Manner of switching for transformers</b>		li0
<b>Verification of suitability</b>		CE / cRUus
<b>Product function</b>		
• temperature surveillance		No
• isolation control		No
• short circuit and overload protection		No
<b>Number of the protective coils</b>		0
<b>Short-term vector power</b>	V·A	5,000
<b>Relative short-circuit voltage</b>	%	2.5

**Inputs:**

<b>Phase number / of the inputs</b>		1
<b>Input voltage</b>		
• _1 / rated value	V	525
• _2 / rated value	V	500

• $I_3$ / rated value	V	475
<b>Electrical input frequency</b>		
• minimum	Hz	50
• maximum	Hz	60

#### Outputs:

<b>Phase number / of the outputs</b>		1
<b>Output voltage</b>		
• $U_1$ / rated value	V	230
<b>Electrical output frequency</b>		
• maximum	Hz	60
• minimum	Hz	50


#### Ambient conditions:

<b>Thermal class / according to IEC 60085</b>		B
<b>Ambient temperature / rated value</b>	°C	40
<b>Protection class IP</b>		IP00

#### Mechanical design:

<b>Design of the electrical connection</b>		
• secondary side / for main current circuit		screw-type terminals / tab terminals
• at the input / for main current circuit		screw-type terminals / tab terminals
<b>Type of mounting</b>		screws
<b>Construction form of the iron core</b>		EI 150/90
<b>Width</b>	m	0.152
<b>Height</b>	m	0.144
<b>Depth</b>	m	0.132

#### Certificates/approvals:

General Product Approval	Shipping Approval	other
<a href="#">ROSTEST</a>	 PR5	<a href="#">Manufacturer</a> <a href="#">other</a>

#### Further information:

##### Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/industrial-controls/catalogs>

##### Industry Mall (Online ordering system)

<http://www.siemens.com/industrial-controls/mall>

##### CAX-Online-Generator

<http://www.siemens.com/cax>

---

**Service&Support (Manuals, Certificates, Characteristics, FAQs,...)**

<http://support.automation.siemens.com/WW/view/en/4AM5742-5FT10-0FA0/all>

---

**Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)**

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=4AM5742-5FT10-0FA0](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=4AM5742-5FT10-0FA0)

---

**last change:**

Aug 25, 2011